

Safety Precautions

Make sure to comply with the safety precautions mentioned hereafter when handling the probe.

Yokogawa Meters & Instruments Co. assumes no responsibility for any consequences resulting from failure to comply with these safety precautions. Also, read the User's Manual of the measuring instrument thoroughly so that you are fully aware of its specifications and handling, before starting to use the probe.

• General definitions of safety symbols and markings



This symbol indicates the risk of injury, death of personnel, or damage to the instrument. Be sure to refer to the corresponding explanation in the User's Manual.



Protective grounding terminal.



Danger. High voltage.

WARNING

This symbol calls attention to a procedure, practice, condition or the like, which, if not correctly performed or adhered to, could result in injury or death of personnel.

CAUTION

This symbol calls attention to a procedure, practice, condition or the like, which, if not correctly performed or adhered to, could result in damage to or destruction of part of the product.

• Make sure to comply with the following safety precautions in order to prevent accidents such as an electric shock which impose serious health risks to the user and damage to the instrument.



WARNING

• Grounding of the measuring instrument

The protective grounding terminal of the measuring instrument must be connected to ground.

• Ground lead of the probe

Make sure to connect the ground lead of the probe to the grounding potential.

• Connecting the object of measurement

Make sure to avoid an electric shock when connecting the probe to the object of measurement. Do not remove the probe from the measuring instrument after the object of measurement is connected.

• Do not operate with suspected failures

If you suspect that there is damage to this probe, have it inspect by a service personnel.

• Nondestructive input voltage range

Do not apply any voltages exceeding ± 40 V(DC+AC peak) between input and earth.

• Must be grounded

Before connecting the input terminal of the probe to the object of measurement ensure that the measuring instrument is properly grounded, that the probe's output connector is attached to the BNC connector of the measuring instrument, and that the ground lead of the probe is properly grounded.

• Do not operate without cover

To avoid electric shock or fire hazard, do not operate this probe with the cover removed.

• Do not operate in wet/damp conditions

To avoid electric shock, do not operate this probe in wet or damp conditions.

• Do not operate in explosive atmosphere

To avoid injury or fire hazard, do not operate this probe in an explosive atmosphere.

• Avoid exposed circuitry

To avoid injury, remove jewelry such as rings, watches, and other metallic objects. Do not touch exposed connections and components when power is present.



CAUTION

• Nondestructive input voltage range

Do not apply any voltages exceeding the Nondestructive input voltage range to the probe.

• Use proper power source

Use the power supply connector for the probe on the DL, DLM, SL, or SB series or use the 700938 or 701934 power supply. Do not operate this probe from a power source that applies more than the voltage specified.

• Terms appear in this manual

Note

Provides information that is important for proper operation of the instrument.


1 Description

The 700939 FET is an active probe with a frequency bandwidth of 900 MHz and attenuation ratio of 10 : 1.


2 Appearance

As shown in the following illustration, the probe consists of a main body and standard accessories.

Various probe applications are possible, depending on the optional accessories that are separately acquired.




Supplied equipment		Accessories	
Name	Part No.	Name	Part No.
1 Probe		6 BNC adapter	700972
2 Ground lead	B9852KL	7, 8 Ground lead	700973
3 Pincher tip	B9852KJ	9 Mini clip adapter	700971
4 IC test tip	B9852BF	10 Printed circuit board adapter	366945
5 Ground attachment	B9852BG	11 Solder-in adapter	366946
		12 Marker tip	B8099DT



3 Specifications

Frequency bandwidth	DC-900 MHz for probe (*1)
Attenuation ratio	10 : 1 ± 2% when connected to a resistance of 50 Ω ± 1% (*1)
Output offset voltage	± 2 mV (± 20 mV when converted into input terminal) (*1)
Input voltage range	10 Vp-p (DC + AC peak should be within ±10V) (*1) (*2)
Nondestructive inputvoltage range	± 40 V (DC + AC peak) (*3)
Input resistance	About 2.5 MΩ
Input capacity	About 1.8 pF
Total cable length	1.5 m (probe cable) 1 m (power supply cable)
Weight	About 180 g
Ambient operating temperature	5 to 40 °C
Ambient operating humidity	20 to 80% RH (no condensation)
Ambient storage temperature	-20 to 60 °C
Ambient storage humidity	20 to 80% RH (no condensation)
Power supply voltage	± 12 V ± 1V (Usable range: 11 to 13 V or -11 to -13 V)
Power supply current	Current of the power supply terminal is less than 125 mA (*2)
EMC Emission	Complying standard : EN61326-1 Class A, EN55011 Class A, Group 1 EMC Regulatory Arrangement in Australia and New Zealand EN 55011 Class A, Group 1 Korea Electromagnetic Conformity Standard (한국 전자파적합성기준) • This product is a Class A (for industrial environment) product. Operation of this product in a residential area may cause radiointerference in which case the user is required to correct the interference.
Immunity	Complying standard : EN61326-1 Table 2 (for use in industrial locations) Susceptibility under immunity condition Noise increase ≤ ±200 mV (*4)



- (*1) Reference operation conditions: Ambient temperature 23 ± 5°C; Ambient humidity 55 ± 10%; 30 minutes after the power supply is applied.
 (*2) When power supply voltage is ± 12 V.
 (*3) For the relation between frequency bandwidth and input voltage derating see the graph on the right.
 (*4) Testing condition:
 Set 20 MHz for the frequency width and 50 Ω for the input coupling of the Oscilloscope.
 Terminate the probe tip with 50Ω.
 Attach a ferrite core (TDK: ZCAT2035-0930A, YOKOGAWA parts number: A1190MN) on each end of the cable.

4 Operation

1. Connect the power supply probe of the product to the power supply connector of DL, DLM, SL, or SB series or to 700938, or 701934.
2. Simply plug-in the BNC output connector to the vertical input of a oscilloscope. In this case set the input resistance of the oscilloscope to 50 Ω.
3. Using the appropriate probe accessories, connect the input to the circuits under measurement.



WARNING

- To protect against electric shock the ground side of the output cable (the shielded side of the BNC connector) must be grounded.
- When disconnecting the BNC connector, always first separate the probe from the high voltage parts of the circuit under measurement.



CAUTION

- Use a soft cloth to clean the dirt. Prevent damage to the probe.
Avoid immersing the probe.
Avoid using abrasive cleaners.
Avoid using chemicals contains benzene or similar solvents.

Note

This device is not specified by any calibration certificate. No test certificate is provided.
 Accurate measurement may not be possible near objects with strong electric fields (like cordless equipment) or strong magnetic fields (like transistors or large current circuits).